SPEAKER ZONE SELECTOR

6 Ch Speaker Zone Selector ZS5601

12 Ch Speaker Zone Selector ZS5121

6 Ch Uninterrupted Speaker Zone Selector ZS5602



ZS5601 and ZS5121 are trusted products for speaker zone selection that provides direct zone switching for single source PA setup via front panel switches or through remote port connected to Amperes PM Series paging desk, or through Amperes TD decoders. Other brands of paging consoles are compatible with ZS provided they have negative triggering switching ports.

ZS5602 shall be suitable for uninterrupted paging setup, ie. when an announcement to a zone is made, other areas with BGM that shall not be interrupted. This will require two sets of amplifiers connected to the ZS5602, thus the system shall consist of two sources, one being BGM and the other as Paging.

Features

ZS5602

- Available in 6 (ZS5601, 5602) and 12 zones (ZS5121) with ALL CALL
- Expansion to more zones if required
- Remote zone triggering port via external paging microphone or console
- Paging override by Amperes paging console with Priority override indicator
- Emergency paging mic triggering port with dry contact for volume controller overriding application
- Flexible amplifier to zone configuration, suitable for 3 or 4 wire systems

Technical Specifications

	ZS5601	ZS5121	ZS5602
Operating voltage	24V DC adaptor via PS9400		
Power consumption	3.5W, 0.14A w All Call	6.8W, 0.28A w All Call	10W, 0.42A w All Call
Max load / channel	500W at 100V line		
Number of zones	6	12	6
Amplifier inputs	6	12	6 BGM ; 6 Paging
Zone selection - Paging	Front panel switch and remote		
Zone selection - BGM	Front panel switch		
Cascade limitation	Unlimited		
Remote triggering	-ve triggered (common ground)		
Indicators	Individual zone switch, Priority		Zone LED
Switching mode	Individua	al, All Call	Individual. All Call
	Local zone selection bypassed when remote		
	trigger is activated		
Dimensions (W x H x D)	482 x 44 x 180 mm		
Weight	1.95 kg	2.10 kg	2.20 kg


Packing information

Carton size : 555 (L) x 295 (W) x 95 (H) mm Gross weight : 7S5601 : 2 55 kg

Gross weight : ZS5601 : 2.55 kg ZS5121 : 2.70 kg ZS5602 : 2.70 kg

1 unit per carton

Rear Views ZS5601 & 5121



Amp - Zone output or Paging out (3 wire)

Remote trigger port

Emergency trigger

